

*KDS021 Standard Motor Sizes and Full Load Amps for Three Phase Induction Motors (415 volts/50 Hz/3 phase)*

<b>Standard Motor Sizes (kW)</b>	<b>Approximate Full Load Current at 415 Volts (Amps)</b>
0.37	1.2
0.55	1.6
0.75	2.0
1.1	2.5
1.5	3.5
2.2	5.0
3.0	6.5
3.7	7.5
4.0	8.4
5.5	11.0
7.5	14.0
11.0	21.0
15.0	28.0
18.5	35.0
22.0	40.0
30.0	55.0
37.0	66.0
45.0	80.0

**Notes:**

- These values are given as a guide only. They may vary depending on the type of motor and the manufacturer.